

**Octave 1**

<i>Note</i>	<i>Réglage fin</i>	<i>Réglage grossier</i>
C	93	13
C+/D-	156	12
D	231	11
D+/E-	60	11
E	155	10
F	2	10
F+/G-	115	9
G	235	8
G+/A-	107	8
A	242	7
A+/B-	128	7
B	20	7

**Octave 2**

<i>Note</i>	<i>Réglage fin</i>	<i>Réglage grossier</i>
C	175	6
C+/D-	78	6
D	244	5
D+/E-	158	5
E	78	5
F	1	5
F+/G-	186	4
G	118	4
G+/A-	54	4
A	249	3
A+/B-	192	3
B	138	3

**Octave 3**

<i>Note</i>	<i>Réglage fin</i>	<i>Réglage grossier</i>
C	87	3
C+/D-	39	3
D	250	2
D+/E-	207	2
E	167	2
F	129	2
F+/G-	93	2
G	59	2
G+/A-	27	2
A	253	1
A+/B-	224	1
B	197	1

**Octave 4**

<i>Note</i>	<i>Réglage fin</i>	<i>Réglage grossier</i>
C	172	1
C+/D-	148	1
D	125	1
D+/E-	104	1
E	83	1
F	64	1
F+/G-	46	1
G	29	1
G+/A-	13	1
A	254	0
A+/B-	240	0
B	227	0

**Octave 5**

<i>Note</i>	<i>Réglage fin</i>	<i>Réglage grossier</i>
C	214	0
C+/D-	202	0
D	190	0
D+/E-	180	0
E	170	0
F	160	0
F+/G-	151	0
G	143	0
G+/A-	135	0
A	127	0
A+/B-	120	0
B	113	0

**Octave 6**

<i>Note</i>	<i>Réglage fin</i>	<i>Réglage grossier</i>
C	107	0
C+/D-	101	0
D	95	0
D+/E-	90	0
E	85	0
F	80	0
F+/G-	76	0
G	71	0
G+/A-	67	0
A	64	0
A+/B-	60	0
B	57	0

**Octave 7**

<i>Note</i>	<i>Réglage fin</i>	<i>Réglage grossier</i>
C	53	0
C+/D-	50	0
D	48	0
D+/E-	45	0
E	42	0
F	40	0
F+/G-	38	0
G	36	0
G+/A-	34	0
A	32	0
A+/B-	30	0
B	28	0

**Octave 8**

<i>Note</i>	<i>Réglage fin</i>	<i>Réglage grossier</i>
C	27	0
C+/D-	25	0
D	24	0
D+/E-	22	0
E	21	0
F	20	0
F+/G-	19	0
G	18	0
G+/A-	17	0
A	16	0
A+/B-	15	0
B	14	0